


Serial Transmission Device Unit

4GR Series T7D1
(OPP4-1D)

DeviceNet Compatible

INSTRUCTION MANUAL

SM-A42224-A



- Read this Instruction Manual before using the product.
- Read the safety notes carefully.
- Keep this Instruction Manual in a safe and convenient place for future reference.

PREFACE

Thank you for purchasing CKD's serial transmission device unit. This Instruction Manual contains basic matters such as installation and usage instructions in order to ensure optimal performance of the product. Please read this Instruction Manual thoroughly and use the product properly. Keep this Instruction Manual in a safe place and be careful not to lose it.

Product specifications and appearances presented in this Instruction Manual are subject to change without notice.

- The product, which uses control valves such as solenoid valves, motor valves, and air operated valves, is intended for users who have basic knowledge about materials, fluids, piping, and electricity. CKD shall not be responsible for accidents caused by persons who selected or used the product without knowledge or sufficient training with respect to control valves.
- Since there are a wide variety of customer applications, it is impossible for CKD to be aware of all of them. Depending on the application or usage, the product may not be able to exercise its full performance or an accident may occur due to fluid, piping, or other conditions. It is the responsibility of the customer to check the product specifications and decide how the product shall be used in accordance with the application and usage.

SAFETY INFORMATION

When designing and manufacturing any device incorporating the product, the manufacturer has an obligation to ensure that the device is safe. To that end, make sure that the safety of the machine mechanism of the device, the fluid control circuit, and the electric system that controls such mechanism is ensured.

To ensure the safety of device design and control, observe organization standards, relevant laws and regulations, which include the following:

ISO4414, JIS B8370, JFPS2008 (the latest edition of each standard),
the High Pressure Gas Safety Act, Industrial Safety and Health Act, other safety rules, organization standards relevant laws and regulations.




In order to use our products safely, it is important to select, use, handle, and maintain the products properly.

Observe the warnings and precautions described in this Instruction Manual to ensure device safety.

Although various safety measures have been adopted in the product, customer's improper handling may lead to an accident. To avoid this:

Thoroughly read and understand this Instruction Manual before using the product.

To explicitly indicate the severity and likelihood of a potential harm or damage, precautions are classified into three categories: "DANGER", "WARNING", and "CAUTION".

 DANGER	Indicates an imminent hazard. Improper handling will cause death or serious injury to people.
 WARNING	Indicates a potential hazard. Improper handling may cause death or serious injury to people.
 CAUTION	Indicates a potential hazard. Improper handling may cause injury to people or damage to property.

Precautions classified as "CAUTION" may still lead to serious results depending on the situation. All precautions are equally important and must be observed.

Other general precautions and tips on using the product are indicated by the following icon.



Indicates general precautions and tips on using the product.

Precautions on Product Use

WARNING

The product must be handled by a qualified person who has extensive knowledge and experience.

The product is designed and manufactured as a device or part for general industrial machinery.

Use the product within the specifications.

The product must not be used beyond its specifications. In addition, never modify or additionally machine this product.

The product is intended for use in devices or parts for general industrial machinery. It is not intended for use outdoors or in the conditions or environment listed below.

(Exception is made if the customer consults with CKD prior to use and understands the specifications of the product. However, even in that case, safety measures must be taken to avoid danger in case of a possible failure.)

- In applications for nuclear power, railroad system, aviation, ship, vehicle, medical equipment, and equipment that directly touches beverage or food.
- For special applications that require safety including amusement equipment, emergency shut-off circuit, press machine, brake circuit, and safety measures.
- For applications where life or properties may be adversely affected and special safety measures are required.

Do not handle the product or remove pipes and devices until confirming safety.

- Inspect and service the machine and devices after confirming the safety of the entire system. Also, turn off the energy source (air supply or water supply) and power to the relevant facility. Release compressed air from the system and use extreme care to avoid water or electric leakage.
- Since there may be hot or live parts even after operation has stopped, use extreme care when handling the product or removing pipes and devices.
- When starting or restarting a machine or device that incorporates pneumatic components, make sure that a safety measure (such as a pop-out prevention mechanism) is in place and system safety is secured.

CONTENTS

PREFACE	i
SAFETY INFORMATION.....	ii
Precautions on Product Use	iii
CONTENTS.....	iv
1. PRODUCT OVERVIEW	1
1.1 System Overview	1
1.1.1 System features	1
1.1.2 System structure	2
1.2 Part Name	3
1.2.1 Parts of the device unit	3
1.2.2 Switches and LED indicators	4
1.3 Specifications	6
1.3.1 Communication specifications	6
1.3.2 Device unit specifications	7
2. INSTALLATION	8
2.1 Mounting	8
2.2 Wiring	9
2.2.1 Connecting and wiring to the network connectors	9
2.2.2 Connecting and wiring to the valve power plug	11
3. USAGE	12
3.1 Setting the Switches	12
3.1.1 Node address setting	13
3.1.2 Baud rate setting	13
3.1.3 Output mode setting	13
3.2 Network configuration with EDS (Electric Data Sheet) file	14
3.2.1 Registering the device	14
3.3 Correspondence between the device unit output number and PLC address No.	15
3.3.1 PLC address correspondence table	15
3.3.2 Examples of valve No. assignments corresponding to the device unit T7D solenoid output No.	16
3.4 Programming	18
3.4.1 Programming	18
3.4.2 Data mapping	18
3.4.3 Device profile	18
3.4.4 Object implementation	19
4. MAINTENANCE AND INSPECTION	23
4.1 Periodic Inspection.....	23
4.2 Removing and Mounting	24
4.2.1 Removing the product (device unit).....	25
4.2.2 Mounting the product (device unit)	25
5. TROUBLESHOOTING	26
5.1 Problems, Causes, and Solutions	26
6. WARRANTY PROVISIONS	27
6.1 Warranty Conditions	27
6.2 Warranty period.....	27

1. PRODUCT OVERVIEW

1.1 System Overview

1.1.1 System features



Make sure to read the instruction manual for each product.
This Instruction Manual mainly describes the device unit (OPP4-1D) for 4GR.
For controller unit and other device units that are connected in the same system as the product, read the instruction manuals issued by each manufacturer.
For manifold solenoid valves, make sure to read both this Instruction Manual and the instruction manual for the solenoid valve to fully understand the functions and performance in order to use the valves correctly.

■ T7D1(OPP4-1D)

T7D1(OPP4-1D) is a device unit for 4GR that can be connected to DeviceNet, an open field network defined by ODVA.

Features include the following:

- The device unit is connected to PLC with only a network cable (DeviceNet dedicated), allowing significant reduction in wiring man-hours.
- When a communication error occurs, the device unit output status can be set by a switch. (Hold all point output/ Clear all points output).
- The number of output points is 16, and up to 63 units can be connected to one controller unit. (When using Configurator).

■ DeviceNet

DeviceNet is a multi-bit, multi-vendor network that combines controls and data on a machine/line-control level.

DeviceNet is maintained and managed by ODVA (Open DeviceNet Vendor Association, Inc).

If you have any questions concerning the DeviceNet system, refer to the following website run by ODVA:

ODVA

Website address is, <https://www.odva.org/>


1.1.2 System structure

This system mainly consists of a PLC, controller unit, T7D1(OPP4-1D) mounted manifold solenoid valve, and peripheral equipment.

Examples of PLC and controller unit combination

PLC manufacturer	Compatible PLC	controller unit model
Omron Corporation	NJ Series	CJ1W-DRM21
	CJ Series	
	CS1 Series	CS1W-DRM21
Other DeviceNet compatible controller units		


Example of basic structure of the system



Controller unit : A unit which controls device and requests to open connection.
 Tap : A device which is used for branch connection.

1.2 Part Name

1.2.1 Parts of the device unit




No.	Part name	Description
①	LED indicators	Indicate the status of the Device Unit and network.
②	Switches	The setting switches are used to set three kinds of functions, node address, baud rate, and output mode if the communication error occurs.
③	Cover	Protects the LEDs and setting switches.
④	Electric power terminal (M3)	Here the main power supply is connected. (Load power supply is included)
⑤	Network connector socket	This is the connector socket for connecting the network cable, which allows the Device Unit to be connected to DeviceNet.
⑥	Mounting screw (M2.5 tapping screw)	This screw is used to secure the Device Unit to the connecting block.

1.2.2 Switches and LED indicators

⚠ CAUTION

Discharge static electricity from your body before touching the product.
Static electricity may cause damage to the product.



■ Switches

The switches are used to set node address, baud rate, and output mode in the event of a communication error.

This Device Unit operates according to the switch settings when the power is turned on.

※Setting changes will not be recognized after the power is turned on.














Name of switch	Content of Setting
NA Switch No.1 to 6 (Node address setting)	Sets the Device Unit node address between 0 to 63.
DR Switch No.7, 8 (Baud rate setting)	Sets the baud rate for the Controller unit.
C H Switch No.10 (Output mode setting)	Selects whether to hold (H) or clear (C) the output status when a communication error occurs.



Note) Switch No. 9 be the unused.

■ LED indicators

These LEDs indicate the status of the product and network.
Refer to the following table for the description of LED indicators.

1) <Module status (MS) / Network status (NS) LED>

MS LED	NS LED	Description		Note
Green 	Green 	I/O communication in progress	I/O data is being communicated between the controller and device unit.	Operating normally.
Green 	●	Node address duplication checking	Waiting for node address duplication checking to be completed at the controller.	In case only the certain device unit is in this condition, restart the unit after checking if the baud rate is the same as the controller.
Green 	Green 	Connection waiting	Waiting for connection establishment from the controller.	
Red 	●	Watchdog timer error	Watchdog timer error occurred in the Device Unit.	Replace the Device Unit.
Red 	●	Improper switch setting	Switch setting is not correct.	Restart the Device Unit after checking the switch setting.
Green 	Red 	Duplicate node address	Node address is duplicated.	After re-setting the node address to avoid duplicate, restart the Device Unit.
Green 	Red 	Bus-off detection	Bus-off	Check the following and restart the Device Unit: <ul style="list-style-type: none"> • Matching controller and device baud rates • Proper cable lengths (trunk and branch lines) • Broken or loose cables • Installation of terminators at both ends of the trunk line • Excessive noise
Green 	Red 	Communication time out		
●	●	No main power supply		After checking both node address and baud rate are set properly, supply the main power supply.

 : ON  : Flashing ● : OFF

1.3 Specifications

1.3.1 Communication specifications

Item	Specifications			
Transfer rate (Baud rate)	Chooseable (125kbps /250kbps /500kbps)			
Communication media (Network cable)	DeviceNet dedicated 5-wire cable signal lines, (2 signal lines, 2 power lines, 1 shielded line)			
Communication distances	Transfer rate (Baud rate)	Network length	Branch line length	Total branch line length
	125kbps	500m max.*1	6m max.	156m max.
	250kbps	250m max. *1	6m max.	78m max.
	500kbps	100m max.	6m max.	39m max.
Communication power supply	11.0 VDC to 25.0 VDC			
Error control method	CRC error check			

*1: These are for Thick cables. Keep the maximum length to 100m or less when using Thin cables.

1.3.2 Device unit specifications

The product must be used within the following specifications.

Item		Specifications
Model No.		T7D1 (OPP4-1D)
Communication power supply voltage		11.0 VDC to 25.0 VDC
Communication power supply current consumption		50 mA or less
Valve power voltage		22.8 VDC to 26.4 VDC (24 VDC +10%, -5%)
Valve power current consumption		110 mA or less
Output type		NPN output (+COM)
Number of input/output point		16
Node address setting		Node address setting by switch [0-63]
Output setting when communication error occurs		Hold all points output (Hold)/ Clear all points output (Clear)
Insulation resistance		Between external terminals and the case: 30 MΩ or more with 500 VDC
Withstand voltage		Between external terminals and the case: 500 VAC for one minute
Shock resistance		294.0 m/s ² for 3 times in 3 directions
Storage ambient temperature		-20°C to 70°C
Storage humidity		30% to 85% RH (no dew condensation)
Ambient temperature		-5°C to 55°C
Ambient humidity		30% to 85% RH (no dew condensation)
Atmosphere		No corrosive gas
Communication protocol		DeviceNet compliant
Output insulation		Photo coupler insulation
Max. load current		40 mA/1 point
Leakage current		0.1 mA or less
Residual voltage		0.5 V or less
Fuse		24V, 1A
Operation indicator		LED (Power supply status and communication status only)
Number of node		1 node
Vibration resistance	Durability	10 Hz to 150 Hz to 10 Hz, 1 octave/min., 15 sweeps each in X, Y, Z directions with 0.75 mm half-amplitude or 98.0 m/s ² , whichever smaller.
	Malfunction	10 Hz to 150 Hz to 10 Hz, 1 octave/min., 4 sweeps each in X, Y, Z directions with 0.5 mm half-amplitude or 68.6 m/s ² , whichever smaller.

2. INSTALLATION

2.1 Mounting

CAUTION

Before handling a DeviceNet device, touch a grounded metal part to discharge static electricity from your body.

Static electricity may cause damage to the product.

Do not apply tension or shocks to the power cable or network cable.

If the wiring is long, the cable weight or shocks may cause an unexpected force and result in damage to the connector or device.

Take appropriate measures such as secure the wiring to the machine or device midway.

To prevent noise problems, keep the following in mind when wiring:

- If noise could have an effect, prepare power for each manifold solenoid valve and wire separately.
- Wire the power cable as short as possible.
- Wire the power cables for the product separately from the power cables for noise-generating devices such as inverter motors.
- Wire the power cable and network cable away from other power lines as much as possible.

Wire the power cable and network cable properly within its specifications.

Incorrect wiring may cause the device unit to malfunction or break.


Make sure that cables and connectors are securely connected before turning on the power.

- 1** Connect the network cable and power cable.
Check all this Instruction Manual, the instruction manuals for PLC and each unit, and connect the cable properly.
Incorrect connection may cause not only a system failure but also serious fault to the other devices.
- 2** Keep 200 mm or more away from high-voltage lines and power lines or wire the high-voltage lines and power lines in metal tubing and ground it before mounting this device unit.

2.2 Wiring

■ The function explanation and the connection destinations of the terminal

Symbol	Function	Objects to be connected	Indicated Cable Color
① V-	Network power supply (-)	Use low-noise DC11 to 25V power supply	Black
② CAN_L	Communications data lines (low)	Connect CAN-L network cable of the controller unit or other device.	Blue
③ Shield	Shield terminal	Cable shielding	—
④ CAN_H	Communications data lines (high)	Connect CAN-H network cable of the controller unit or other device.	White
⑤ V+	Network power supply (+)	Use low-noise DC11~25V power supply	Red
⑥ Power input	Main power supply (Including load power supply)	DC24V \pm 10%	0V
			24V



2.2.1 Connecting and wiring to the network connectors

⚠ WARNING

Carry out wiring with the power turned off.

An electric shock may occur by touching the electrical wiring connection (bare live part).

Do not touch live parts with bare hands.

An electric shock may occur.

Thoroughly read and understand this instruction manual before working on electrical wiring.

⚠ CAUTION

Check the working voltage and polarity before wiring and energizing.

Take measures against lightning surges on the device side.

The product has no resistance to lightning surges.

Use a dedicated network cable that complies with DeviceNet specifications.

Provide sufficient bending radius for the network cable and do not bend it forcibly.

Separate the network cable from power lines and high-voltage lines.

Use a DeviceNet dedicated network cable, and make sure to understand these specifications before wiring. For details, refer to the instruction manual of the controller unit manufacturer or ODVA.

Recommended network cable: DeviceNet dedicated cable

Manufacturer	Cable	Model
Omron Corporation	DeviceNet Compatible cable	DCA2-5CN series


Recommended connector

Manufacturer	Connector	Remark
Phoenix contact	TMSTBP2.5/5-STF-5.08AUM	Supplied connector with connector fixing screw
Phoenix contact	TMSTBP2.5/5-ST-5.08AUM	Similar connector without connector fixing screw

■ Connecting the network cables

When connecting the DeviceNet cable to this product, follow the steps below

- 1 After confirming safety, stop network communication and turn off all peripheral equipment.
- 2 Insert each of the DeviceNet cable wires, CAN H (white), CAN L (blue), V+(red), V-(black), and Drain into relevant hole(CAN H ,CAN L ,V+ , V- , and Drain) while carefully referring to the orientation of the attached connection connector (TMSTBP2.5/5-STF-5.08AUM). (Refer to the figure below)
- 3 Firmly tighten each cable, using the cable fixing screw of connecting connector. (Adequate tightening torque : 0.5N·m)
- 4 Make sure the color of the connector cable and supplied connector are the same color, the connector plugged into the product, please tighten the screws firmly. (Adequate tightening torque : 0.3N·m)



2.2.2 Connecting and wiring to the valve power plug

CAUTION

Always check the polarity and rated voltage thoroughly before connecting cables.

Calculate the current consumption to select the power cable.

Consider the voltage drop due to cables when selecting and wiring the cables if power is supplied to more than one device unit from one power supply.

Take measures to secure the specified power supply voltage if voltage drop cannot be avoided.

For example, wire the power cables in multiple systems or install other power supplies to secure the specified power supply voltage.

Use a terminal block when crossover wiring power cables.

■ Connecting the power cables

When connecting the power cable to the Device Unit, follow the procedure described below.

- 1** After confirming safety, turn off the power to connect to the Device Unit.
- 2** Attach an M3 crimp terminal that is not more than 6mm in width to the power cable.
- 3** Secure the power cable to the power supply terminal by matching the polarities, that is, 24V wire to 24V terminal (+ terminal) and 0V wire to 0V terminal (—terminal).
(Adequate tightening torque : 0.5N·m).

In this product (OPP4), the Device Station (unit) power supply and load (valve) power supply are common, which cannot be separate from each other.

3. USAGE

WARNING

Consult CKD about the specifications before using the product under conditions not specified for the product or for special applications.

CAUTION

Thoroughly read and understand the instruction manual for the network system to be used before using the serial transmission device unit.

Carefully check the address setting value of serial transmission device unit before use.

Improper address setting value may cause valves or cylinders to malfunction.

Be careful of the surroundings and ensure safety before turning on or off the power.

The system or solenoid valve (cylinder) may operate suddenly.

3.1 Setting the Switches

CAUTION

Discharge static electricity from your body before touching the product.

Static electricity may cause damage to the product.

Set switches while communication power is turned off.

Since switch settings are read when the power is turned on, changes made to the settings after turning on the power are not recognized.

Keep the cover of serial transmission device unit closed except when setting the switches.

The cover may become damaged or foreign matters may enter inside and cause unexpected failure.

Be careful not to allow any foreign matter to enter inside when setting the switches.

Unexpected failure may result.

Do not handle switches roughly.

Switches are precision devices and can be easily damaged.

Do not touch the internal circuit board when setting the switches.

The internal circuit board can be easily damaged.

3.1.1 Node address setting

Set the Device Unit node address.

The Device Unit functions according to the node address setting at power-up.

Duplicate node address cannot be assigned.


Node address	Switch No.					
	1 (32)	2 (16)	3 (8)	4 (4)	5 (2)	6 (1)
0	0	0	0	0	0	0
1	0	0	0	0	0	1
2	0	0	0	0	1	0
3	0	0	0	0	1	1
⋮	⋮					
60	1	1	1	1	0	0
61	1	1	1	1	0	1
62	1	1	1	1	1	0
63	1	1	1	1	1	1

0 : OFF 1 : ON Value in () is indicated on the sheet.

*Example to set the node address to "50":

$$50 = 32 \cdot (\text{SW1 ON}) + 16 \cdot (\text{SW2 ON}) + 8 \cdot (\text{SW3 OFF}) + 4 \cdot (\text{SW4 OFF}) + 2 \cdot (\text{SW5 ON}) + 1 \cdot (\text{SW6 OFF})$$

According to the above formula, turn ON the switch Nos.1, 2, and 5, and turn OFF other switches (Nos.3, 4, and 6).



3.1.2 Baud rate setting

Set the baud rate for the controller unit.

baud rate	Switch No.	
	7 (DR1)	8 (DR0)
125 kbps	0	0
250 kbps	0	1
500 kbps	1	0
Cannot be set	1	1

0 : OFF 1 : ON Value in () is indicated on the sheet.

3.1.3 Output mode setting

The output data status if the communication error occurs in this product is set as shown below.

Output mode	Switch No.10 (CH)	Content of Setting
CLEAR	OFF	Used to clear to "0" all the output data from the controller unit in case of a communication error.
HOLD	ON	Used to hold the output data in the status immediately before the data is output from the controller unit in case of a communication error.

3.2 Network configuration with EDS (Electric Data Sheet) file

In order for the DeviceNet device to join the network, it is necessary to register the communication specification of the device to the network using the EDS file. Refer to the instruction manual issued by the controller unit manufacturer for registering the EDS file. Also, to ensure a suitable network configuration, use the latest EDS file complying with the model or product version.

3.2.1 Registering the device

Check the address and specifications (model name) of the device before registering, as both the device and EDS file will need to be matched first.

Refer to the following table for the device specifications and EDS file.

Specifications and the EDS files

Item	Specifications
Manifold Model No.	-T7D1
Single unit model no.	OPP4-1D
Output type	+COM (NPN)
I/O points	16 points output
Name of EDS file	CKD_ OPP4-1D _v20.05.eds

3.3 Correspondence between the device unit output number and PLC address No.

3.3.1 PLC address correspondence table

This correspondence table uses OMRON PLC as an example.

<T7D1 (16 points output)>

Assigned address to the PLC memory	Output Bit 00-15															
	00	01	02	03	04	05	06	07	08	09	10	11	12	13	14	15
device unit output No.	0	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15
Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16


3.3.2 Examples of valve No. assignments corresponding to the device unit T7D solenoid output No.

In the table below, each valve number consists of a number (the station number) and an alphabet (the a-side solenoid or the b-side solenoid). For example, “1a” refers to 1st station a-side solenoid. Also, “E” stands for “Empty”.

Manifold stations are numbered from left to right with the piping port towards the user (refer to the figure below).

As appearance and maximum number of stations differ depending on the solenoid valve model, check individual specifications.

<T7D1 (16 points output)>



The figure is an example of mounting eight stations of double-solenoid type valves. There is no solenoid on the b-side for single-solenoid type.

Standard wiring

• Single solenoid valve

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	2a	3a	4a	5a	6a	7a	8a	9a	10a	11a	12a	13a	14a	15a	16a

• Double solenoid valve

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b

• Mixed (both single and double solenoid valves are mounted) [example]

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	2a	3a	3b	4a	4b	5a	6a	7a	7b	8a	9a	10a	10b	11a	11b

Double wiring

- Single solenoid valve

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	(E)	2a	(E)	3a	(E)	4a	(E)	5a	(E)	6a	(E)	7a	(E)	8a	(E)

- Double solenoid valve

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	1b	2a	2b	3a	3b	4a	4b	5a	5b	6a	6b	7a	7b	8a	8b

- Mixed (both single and double solenoid valves are mounted) [example]

Solenoid output No.	s1	s2	s3	s4	s5	s6	s7	s8	s9	s10	s11	s12	s13	s14	s15	s16
Valve no.	1a	(E)	2a	(E)	3a	3b	4a	4b	5a	(E)	6a	(E)	7a	7b	8a	(E)

3.4 Programming

3.4.1 Programming

This device unit is treated as a device unit device with 16 points output.

This device unit acts as an output device which transmits output data to valves after receiving it from the controller unit.

Refer to the manual provided by the PLC manufacturer when programming.

Execute the programming by referring to the following table for I/O mapping.

The characteristics of this device unit such as output status setting when an error occurs, and the +COM/-COM output specifications, have no relevance to the programming.

3.4.2 Data mapping

Output data mapping

I/O points	Output data	Bit															
		<u>0</u>	<u>1</u>	<u>2</u>	<u>3</u>	<u>4</u>	<u>5</u>	<u>6</u>	<u>7</u>	<u>8</u>	<u>9</u>	<u>10</u>	<u>11</u>	<u>12</u>	<u>13</u>	<u>14</u>	<u>15</u>
16 points	2bytes	00	01	02	03	04	05	06	07	08	09	10	11	12	13	14	15

3.4.3 Device profile

General device data	Compatible DeviceNet Specifications	Volume One – Edition 3.26 Volume Three – Edition 1.15
	Vendor name	CKD Corporation (ID=0xC9)
	Device type	Pneumatic Valve(s)
Physical conformance data	Communication power supply current consumption	24 VDC 40 mA or less
	Connector style	Sealed micro connector
	Insulation at physical layer	None
	Supported indicators	Module, Network
	MAC ID setting	Dip switch
	Default MAC ID	1
	Setting baud rate	Dip switch
Communications data	Supported baud rate	125kbps/250kbps/500kbps
	Predefined Controller / Device connection set	Group 2 Only Server
	Dynamic connections support (UCMM)	None
	Explicit message fragmentation support	Yes

3.4.4 Object implementation

- Identity Object (0x01)

Object class	Attribute	Not supported
	Services	Not supported

Object instance 1 (0x01)	Attribute		ID content	Explicit Message transmission		Value
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set	T7D1
	1	0x01	Vender ID	Enable	Disable	201 (0xC9)
	2	0x02	Device Type	Enable	Disable	27(0x1B) Pneumatic Valve(s)
	3	0x03	Product Code	Enable	Disable	40
	4	0x04	Revision	Enable	Disable	20.05
	5	0x05	Status	Enable	Disable	bit 0 only
	6	0x06	Serial Number	Enable	Disable	Unique for each Unit
	7	0x07	Product Name	Enable	Disable	OPP4-1D
Services	DeviceNet Services		Parameter options			
	0x05	Reset	None			
	0x0E	Get_Attribute_Single	Yes			

- Message Router Object (0x02)

Object class	Attribute	Not supported
	Services	Not supported
Object instance	Attribute	Not supported
	Services	Not supported
Vendor specific additions		None

● DeviceNet object (0x03)

Object class	Attribute		ID content	Explicit Message transmission		Value
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set	
	1	0x01	Revision	Enable	Disable	
Services		DeviceNet Services		Parameter options		
		0x0E	Get_Attribute_Single	Yes		

Object instance 1 (0x01)	Attribute		ID content	Explicit Message transmission	
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set
	1	0x01	MAC ID	Enable	Disable
	2	0x02	Baud rate	Enable	Disable
	3	0x03	BOI	Disable	Disable
	4	0x04	Bus-off Counter	Enable	Disable
	5	0x05	Allocation information	Enable	Disable
	6	0x06	MAC ID Switch Changed	Enable	Disable
	8	0x08	MAC ID Switch Value	Enable	Disable
	10	0x0A	Quick Connected	Enable	Enable
Services		DeviceNet Services		Parameter options	
		0x0E	Get_Attribute_Single	Yes	
		0x10	Set_Attribute_Single	Yes	

* 1 "Set" is enable only when software mode and NA switch is set to 64 or more (see "3.1.3 Software mode")

* 2 "Set" is enable only at software mode.

● Assembly Object (0x04)

Object class	Attribute		ID content	Explicit Message transmission		Value
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set	
	1	0x01	Revision	Enable	Disable	2
Services		DeviceNet Services		Parameter options		
		0x0E	Get_Attribute_Single	Yes		
		0x10	Set_Attribute_Single	Yes		

Object instance	Attribute		ID content	Explicit Message transmission	
	Decimal (Dec)	Hexadecimal (Hex)	-	T7D1	
				Get	Set
15 (0x0F)	3	0x03	Data	-	-
35 (0x23)	3	0x03	Data	Enable	Enable
37 (0x25)	3	0x03	Data	-	-
Services		DeviceNet Services		Parameter options	
		0x0E	Get_Attribute_Single	Yes	
		0x10	Set_Attribute_Single	Yes	

● Connection object (0x05)

Object class	Attribute	Not supported
	Services	Not supported

	Attribute		ID content	Explicit Message transmission		Value
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set	
Object instance 1 (0x01) Explicit	1	0x01	State	Enable	Disable	-
	2	0x02	Instance Type	Enable	Disable	0x00
	3	0x03	Transport class trigger	Enable	Disable	0x83
	4	0x04	Produced connection ID	Enable	Disable	Unique for each Unit
	5	0x05	Consumed connection ID	Enable	Disable	Unique for each Unit
	6	0x06	Initial comm characteristics	Enable	Disable	0x21
	7	0x07	Produced connection size	Enable	Disable	0x0C00
	8	0x08	Consumed connection size	Enable	Disable	0x1300
	9	0x09	Expected packed rate	Enable	Enable	0xC409
	12	0x0C	Watchdog time-out action	Enable	Disable	1
	13	0x0D	Produced connection path length	Enable	Disable	0
	15	0x0F	Consumed connection path length	Enable	Disable	0
	17	0x11	Production inhibit time	Enable	Disable	0
	18	0x12	Connection_timeout_multiplier	Enable	Disable	0
Services	DeviceNet Services		Parameter options			
	0x0E	Get_Attribute_Single	Yes			
	0x10	Set_Attribute_Single	Yes			

	Attribute		ID content	Explicit Message transmission		Value
	Decimal (Dec)	Hexadecimal (Hex)	-	Get	Set	T7D1
Object instance 2 (0x02) Poll	1	0x01	State	Enable	Disable	-
	2	0x02	Instance Type	Enable	Disable	0x01
	3	0x03	Transport class trigger	Enable	Disable	0x82
	4	0x04	Produced connection ID	Enable	Disable	Unique for each Unit
	5	0x05	Consumed connection ID	Enable	Disable	Unique for each Unit
	6	0x06	Initial comm characteristics	Enable	Disable	0x01
	7	0x07	Produced connection size	Enable	Disable	0x0000
	8	0x08	Consumed connection size	Enable	Disable	0x0002
	9	0x09	Expected packed rate	Enable	Enable	0x0000
	12	0x0C	Watchdog time-out action	Enable	Enable	0x0000
	13	0x0D	Produced connection path length	Enable	Disable	0x0000
	15	0x0F	Consumed Connection path length	Enable	Disable	0x06
	16	0x10	Consumed connection path	Enable	Disable	20_04_24_23_30_03 (Hex)
	17	0x11	Production inhibit time	Enable	Disable	0x0000
Services	DeviceNet Services			Parameter options		
	0x0E	Get_Attribute_Single		Yes		
	0x10	Set_Attribute_Single		Yes		

4. MAINTENANCE AND INSPECTION

WARNING

Turn off the power, stop the supply of compressed air and make sure that there is no residual pressure before conducting maintenance.

Do not disassemble, modify, or repair the product.

These may cause failure or malfunction.

CAUTION

Regularly perform daily and periodic inspections to correctly maintain product performance.

If maintenance is not properly managed, the product's functions may deteriorate significantly and this may lead to faults (such as short service life, damage, and malfunction) or accidents.

Do not drop or apply excessive vibrations or shocks to the product.

These may cause damage because parts inside the product are made to precise specifications.

4.1 Periodic Inspection

This section describes the cleaning and inspection of the device unit for daily maintenance and what to do when replacing the unit. Conduct the periodic cleaning and inspection to use the product in the optimum condition.

■ Cleaning

- 1** For daily cleaning, wipe the product with a soft dry cloth.
- 2** When stains cannot be removed by wiping with a dry cloth, moisten the cloth with diluted neutral detergent (2%), wring it, and wipe the stains again.
- 3** Objects such as rubber, vinyl, or tape may stain the device unit if they are left in contact with the unit for a long period. Remove such objects when cleaning if they are leaving stain on the product.

■ Inspection

Conduct inspection once or twice a year.

If using the product in an environment where temperature or humidity is extremely high or in a dusty environment, conduct inspections at a shorter interval.

<Inspection items>

Inspect the following items to make sure that each item satisfies the criteria.

If any item does not meet the criteria, improve the surrounding environment or adjust the unit.

Inspection items	Inspection details	Criteria	Inspection method
Environment	Is the surrounding and in-panel temperature appropriate?	Refer to "1.3.2 Device unit specifications".	Thermometer
	Is there any accumulated dust?	No dust	Visual inspection
Installation	Is the device unit fixed securely?	No looseness	Hexagonal wrench
	Is the power cable connector fully inserted?	No looseness	Visual inspection
	Is the network cable connector fully inserted?	No looseness	Visual inspection
	Is the connection cable not broken?	No abnormality in appearance	Visual inspection

■ Checking the device unit before/after replacing

Each unit (controller and device) is a device that constitutes a part of a network.

If any unit fails, immediately perform recovery work to prevent the entire network from being affected. To restore the network function as fast as possible, it is recommended to prepare spare units.

<Inspection items>

If a fault is detected and the unit is replaced with a new one, check if the new unit has no abnormality. Also, confirm the device unit settings.

<Settings for replacement device unit>

For the switches on the replacement device unit, confirm the specifications and set the same settings as the previous unit.

4.2 Removing and Mounting

WARNING

Turn off the power and completely release the pressure before removing or adding a manifold solenoid valve.

Thoroughly read and understand this Instruction Manual before removing and adding the manifold solenoid valve.

Do not touch the electrical wiring (bare live part).

An electric shock may occur.

Do not touch live parts with bare hands.

An electric shock may occur.

CAUTION

Check the device unit node address and the setting made to specify which action to take on the output in the event of communication error before turning on the communication power.

Do not attach or detach the connector while the power is turned on.


These may cause failure or malfunction.

Do not pull out the device unit by pulling the cable or connector.

This may cause cable disconnection or damage.

4.2.1 Removing the product (device unit)

- 1** After confirming safety, stop network communication as necessary and turn off all peripheral equipment.
- 2** After confirming safety, turn off the main power and network power as necessary.
- 3** Loosen the Device Unit fixing screws
- 4** Hold and pull out the product slowly in the direction of the arrow.
- 5** Remove the network connectors and power cable.



4.2.2 Mounting the product (device unit)

- 1** Set the node address of the product.
- 2** Holding the Device Unit, insert it into the Device Unit connecting block slowly from the front along the guide.
- 3** Make sure the Device Unit and the connecting block are connected and tighten the Device Unit mounting screw firmly. (Adequate tightening torque: 0.5 N·m)
- 4** Turn off the power (for main/network/) and connect the network connectors and power cable. The system may operate suddenly if the connectors are installed while the power is turned on. Be careful of the surroundings and secure safety before performing work.
- 5** After confirming safety, turn on each power.

5. TROUBLESHOOTING

5.1 Problems, Causes, and Solutions

Troubleshooting for this device unit must be carried out not only for the single unit but for the entire system.

The system may start operating suddenly depending on the communication state. Use extreme care and ensure safety during maintenance.

■ **Fault 1: MS LED does not light up.**

- Check that the power cable is properly connected and in good condition.
- Check if the supplied power voltage is within the specified range.

■ **Fault 2: MS and NS LEDs are not green (IO communication is not running)**

- Refer to the [1.2.2 Switches and LED indicators].

■ **Fault 3: Values of NA switches and DR switch and HC switch are not applied.**

- Power on the switch again after setting.

6. WARRANTY PROVISIONS

6.1 Warranty Conditions

■ Scope of warranty

If the product specified herein fails for reasons attributable to CKD within the warranty period specified below, CKD will promptly provide a replacement for the faulty product or a part thereof or repair the faulty product at one of CKD's facilities free of charge.

Note that the following failures are excluded from the warranty scope:

- Failure caused by handling or use of the product under conditions and in environments not conforming to those stated in the catalog, the Specifications, or this Instruction Manual.
- Failure caused by incorrect use such as careless handling or improper management.
- Failure not caused by the product.
- Failure caused by use not intended for the product.
- Failure caused by modifications/alterations or repairs not carried out by CKD.
- Failure that could have been avoided if the customer's machinery or device, into which the product is incorporated, had functions and structures generally provided in the industry.
- Failure caused by reasons unforeseen at the level of technology available at the time of delivery.
- Failure caused by acts of nature and disasters beyond control of CKD.

The warranty stated herein covers only the delivered product itself. Any loss or damage induced by failure of the delivered product is excluded from this warranty.

■ Confirmation of product compatibility

It is the responsibility of the customer to confirm compatibility of the product with any system, machinery, or device used by the customer.

■ Others

The terms and conditions of this warranty stipulate basic matters.

When the terms and conditions of the warranty described in individual specification drawings or the Specifications are different from those of this warranty, the specification drawings or the Specifications shall have a higher priority.

6.2 Warranty period

The product is warranted for one year from the date of delivery to the location specified by the customer.s